


# CASAMBI Bluetooth Lichtsteuerung konfigurierbar mit IP65 Schutz

## CASAMBI Bluetooth Lighting Control Configurable with IP 65 Protection



CASAMBI  
READY

IP65

CE

SELV

### Technische Daten *Technical data*

(DALI: CCT, RGB, RGB+W, 1..4CH; 0-10V)

Artikelnummer Einbaugehäuse <i>Part no built in housing</i>	808685
Typ Einbaugehäuse <i>Type built in housing</i>	IIBTPRO
Versorgungseingang <i>Power supply input</i>	220..240 V; 50 Hz
Signaleingang <i>Signal input</i>	Bluetooth 4.0 lite @ Smart-Geräte / <i>smart devices</i>
Funksignal <i>Radio signal</i>	2,4..2,483 GHz; 4 dBm
Signalausgang <i>Signal output</i>	DALI / 0-10V, max. 7 mA; SELV; kurzschlussgeschützt / <i>short circuit protection</i>
Umgebungstemperatur <i>Ambient temperature (ta)</i>	-20..+40 °C
Max. Bemessungstemperatur <i>Rated Max. temp. (tc)</i>	70 °C
Schutzgrad IP <i>IP Protection Level</i>	65
Abmessungen <i>Dimensions</i>	100x37 mm (ohne Kabel)

- Feste Gummi-Anschlußleitungen, je 15cm
- Schnittstelle mit IP65 Schutz zum komfortablen Regeln von LED-Netzteilen mit DALI Signaleingang durch Tablet oder Smartphone (Apple, Android) über Bluetooth
- Sendet DALI broadcast. Konfigurieren der anderen Schnittstellen-Typen I(U)BTU, I(U)...BTDA möglich vor Koppeln ins Netzwerk: Profil ändern
- Kostenlose App von CASAMBI (Apple / Android):
  - Regeln der Helligkeit und Lichtfarbe
  - Konfigurieren von Leuchten und Leuchten-Netzwerken
  - Erstellen von Szenen und Animationen (Farbverläufe)
  - Neue Geräte werden automatisch erkannt
  - Intelligente Timer- und Galeriefunktionen
  - Freigabeoptionen festlegen (nur ich, alle, nur mit Passwort, ..)
- Gateway wird nicht benötigt, Einrichtung aber möglich
- Integrierte Antenne  
(Zeichnung grauer Bereich, nicht mit Metallgehäuse abdecken)
- Auch steuerbar über Netzschalter oder Wandschalter RWBT Xpress und RW...EBT
- Apple Watch kompatibel

- Fixed rubber connection cables, each 15cm
- Easily operated interface with IP65 protection to control LED controlgear with DALI signal by smartphone or tablet (Apple, Android) via Bluetooth
- Sends DALI broadcast. Configuration of the other interface types I(U)BTU, I(U)...BTDA is possible before pairing to a network: change profile
- Free App from CASAMBI (Apple / Android):
  - lighting control (color / dim level)
  - configuration of luminaires and luminaires networks
  - creation of scenes and animations (color gradient)
  - automatic detection of new devices
  - intelligent timer and gallery function
  - protection settings of your luminaires network (just me, with password, ..)
- You can setup a gateway but it is not necessary
- Integrated antenna (drawing grey marking, do not cover with metal case)
- Also controllable via mains switch or wall switch RWBT Xpress and RW...EBT
- Apple Watch compatible


App for  
iOS



App for  
Android



PDF



# CASAMBI Bluetooth Lichtsteuerung konfigurierbar mit IP65 Schutz

## CASAMBI Bluetooth Lighting Control Configurable with IP65 Protection

### Anschlusschemen: Connection schemes:

