


Regelbare Lampenfassung mit CASAMBI Bluetooth Lichtsteuerung

Controllable Lampholder with CASAMBI Bluetooth Lighting Control



CASAMBI
INSIDE

CE

E

Technische Daten <i>Technical data</i>	Glattmantel	Gewindemantel	Flanschmantel
	<i>Plain shell</i>	<i>Threaded shell</i>	<i>Partly threaded shell</i>
Artikelnummer <i>Part no</i>	800162	800163	800164
Typ <i>Type</i>	A800TPBT230-50	A801TPBT230-50	A802TPBT230-50
Versorgungseingang <i>Power supply input</i>	220..240 V		
Signaleingang <i>Signal input</i>	Bluetooth 4.0 lite @ Smart-Geräte / <i>smart devices</i>		
Funksignal <i>Radio signal</i>	2,4..2,483 GHz; 4 dBm		
Frequenz <i>Frequency</i>	50..60 Hz		
Leistung bei 230 V <i>Power at 230 V</i>	1..50 W		
Umgebungstemperatur <i>Ambient temperature (ta)</i>	-20..+30 °C		
Schutzgrad IP <i>IP Protection level</i>	20		
Abmessungen <i>Dimensions</i>	38x89 mm	40x89 mm	46x89 mm

- Lampenfassung E27 mit integriertem Dimmer zum komfortablen Regeln von Lichtquellen durch Tablet oder Smartphone (Apple, Android) über Bluetooth
- Zum Betrieb von Glühlampen, dimmbaren LED-Leuchtmitteln, und dimmbaren CFL-Lampen
- Kostenlose App von CASAMBI (Apple / Android):
 - Regeln der Helligkeit und Lichtfarbe
 - Konfigurieren von Leuchten und Leuchten-Netzwerken
 - Erstellen von Szenen und Animationen (Farbverläufe)
 - Neue Geräte werden automatisch erkannt
 - Intelligente Timer- und Galeriefunktionen
 - Freigabeoptionen festlegen (nur ich, alle, nur mit Passwort, ..)
- Gateway wird nicht benötigt, Einrichtung aber möglich
- Integrierte Antenne
- Auch steuerbar über Netzschalter oder Wandschalter RWBT Xpress und RW...EBT
- Apple Watch kompatibel
- Leiter 0,5-1,5mm², 6-8mm abisoliert, AE
- Verschmutzungsgrad: 2
- Passende Zugentlaster und Schraubringe finden Sie in unserem Sortiment

- Easily operated E27 lampholder with dimmer to control lamps with smartphone or tablet (Apple, Android) via Bluetooth
- For operation of incandescent lamps, dimmable LED lamps and dimmable CFL lamps
- Free App from CASAMBI (Apple / Android):
 - lighting control (color / dim level)
 - configuration of luminaires and luminaires networks
 - creation of scenes and animations (color gradient)
 - automatic detection of new devices
 - intelligent timer and gallery function
 - protection settings of your luminaires network (just me, with password, ..)
- You can setup a gateway but it is not necessary
- Integrated antenna
- Also controllable via mains switch or wall switch RWBT Xpress and RW...EBT
- Apple Watch compatible
- Wire 0.5-1.5mm², strip 6-8mm, ferrules
- Pollution degree: 2
- Matching strainers and shade holder rings you will find in our assortment

App for
iOS



App for
Android



PDF

